

ABSTRAKT INSTRUMENTS VS-1 DIY BOM

MAINBOARD						
DESCRIPTION	DESIGNATOR	QTY	MANUFACTURER	VENDOR	PART NUMBER	
Resistor 1k	R2, R12, R14, R16, R19, R28, R31, R32, R150, R167	10	Stackpole	Digikey	RNF18FTD1K00	
Resistor 3.3k	R99, R102, R105, R108, R111, R115, R119, R123	8	Stackpole	Digikey	RNF18FTD3K30	
Resistor 4.7k	R9, R26, R187	3	Stackpole	Digikey	RNF18FTD4K70	
Resistor 5.11k 1%	R5, R22	2	Stackpole	Digikey	RNF18FTD5K11	
Resistor 10k	R76, R80, R88, R92, R188	5	Stackpole	Digikey	RNF18FTD10K0	
Resistor 15k	R3, R4, R11, R15, R20, R21, R29, R34, R97, R100, R103, R106, R109, R113, R117, R121	16	Stackpole	Digikey	RNF18FTD15K0	
Resistor 20k 1%	R7, R24	1	Stackpole	Digikey	RNF18FTD20K0	
Resistor 22.1k	R112, R116, R120, R124, R151, R168	6	Stackpole	Digikey	RNF18FTD22K1	
Resistor 33k	R75, R79, R87, R91, R185, R186	6	Stackpole	Digikey	RNF18FTD33K0	
Resistor 68k	R131, R136, R152, R169	4	Stackpole	Digikey	RNF18FTD68K0	
Resistor 75k	R148, R165	2	Stackpole	Digikey	RNF18FTD75K0	
Resistor 100k	R1, R10, R13, R17, R18, R27, R30, R33, R35, R36, R37, R38, R39, R40, R41, R42, R43, R44, R45, R46, R47, R48, R49, R50, R51, R52, R53, R56, R57, R58, R59, R60, R61, R62, R63, R64, R65, R66, R68, R69, R70, R71, R72, R73, R74, R78, R81, R82, R83, R85, R86, R90, R93, R94, R95, R98, R101, R104, R107, R110, R114, R118, R122, R129, R138, R142, R143, R144, R145, R159, R160, R161, R162, R163, R189	74	Stackpole	Digikey	RNF18FTD100K	
Resistor 150k	R149, R166	2	Stackpole	Digikey	RNF18FTD150K	
Resistor 200k	R147, R164	2	Stackpole	Digikey	RNF18FTD200K	
Resistor 220k	R127, R135	2	Stackpole	Digikey	RNF18FTD220K	
Resistor 330k	R130, R137	2	Stackpole	Digikey	RNF18FTD330K	
Resistor 470k	R8, R25, R128, R139	4	Stackpole	Digikey	RNF18FTD470K	
Resistor 511k	R6, R23	2	Stackpole	Digikey	RNF18FTD511K	
Resistor 820k	R54, R55, R66, R67, R77, R84, R89, R96	8	Stackpole	Digikey	RNF18FTD820K	
Resistor 1M	R126, R134	2	Stackpole	Digikey	RNF18FTD1M00	
Resistor 1.5M	R153, R170	2	Stackpole	Digikey	RNF18FTD1M50	
Resistor 2.2M	R154, R171	2	Stackpole	Digikey	RNF18FTD2M20	
Capacitor 10pF	C80	1	TDK	Digikey	FG28COG1H100DNT0	
Capacitor 100pF	C72, C78	2	TDK	Digikey	FG28COG1H101JNT06	
Capacitor 470pF	C1, C5, C10, C12, C17, C21, C25, C28	8	TDK	Digikey	FG28COG1H471JNT06	
Capacitor 1nF	C42, C52	2	Panasonic	Digikey	ECQ-E12102J	
Capacitor 0.01uF	C75, C76	2	Panasonic	Digikey	ECQ-E2103J	
Capacitor 0.022uF	C2, C6, C9, C13, C18, C22, C26, C29	8	Panasonic	Digikey	ECQ-E2223J	
Capacitor 0.047uF	C71B	1	Panasonic	Digikey	ECQ-E2473J	
Capacitor 0.1uF	C4, C8, C11, C14, C20, C24, C27, C30, C73, C74, C77	11	Panasonic	Digikey	ECQ-E2104J	
Capacitor 0.33uF	C71A	1	Panasonic	Digikey	ECQ-E2333J	
Capacitor 10uF	C79, C82	2	Panasonic	Digikey	ECE-A1EKA100I	
Capacitor 47uF	C81, C83	2	Panasonic	Digikey	ECA-1EM470I	
Diode DO-34	D2, D3	2	Farichild	Digikey	1N4148	
Header, 20x2	CN7B	1	Molex	Digikey	63453-140LF	
Op Amp, Quad JFET	IC1, IC3, IC5, IC7	4	TI	Digikey	LF347N	
Op Amp, Quad JFET	IC9, IC10, IC11, IC42, IC43	5	TI	Digikey	TL084CN	
OTA, Dual	IC2, IC4, IC6, IC8, IC12, IC13, IC14, IC15	9	Col Audio	Digikey	V13700	
Logic Latch	IC16, IC19, IC22, IC25, IC28, IC31, IC34, IC37, IC40	9	TI	Digikey	SN74HC174N	
Analog Switch	IC17, IC18, IC20, IC21, IC23, IC24, IC26, IC27, IC29, IC30, IC32, IC33, IC35, IC36	14	Vishay	Digikey	DG409DI-E3	
Analog Switch	IC38, IC39	2	Vishay	Digikey	DG408DI-E3	
Analog Switch	IC41	1	TI	Digikey	SN74LV4051AN	
Op Amp, Dual JFET	IC100	16	TI	Digikey	TL072CP	
Transistor, BJT, PNP	Q1, Q3, Q5, Q6, Q7, Q8, Q9, Q10, Q11, Q12, Q13, Q14, Q15, Q16, Q18, Q21	16	On Semi	Digikey	BC557B	
Transistor, BJT, NPN	Q2, Q4, Q19, Q20, Q22, Q23, Q24	7	On Semi	Digikey	BC547B	
Transistor, NJFET	Q17, Q20	2	On Semi	Digikey	J112	
Trimmer 10k	TM1, TM2	2	Bourns	Digikey	3362P-1-103LF	
Trimmer 100k	TM3, TM4	2	Bourns	Digikey	3362P-1-104LF	
IC socket, 14pin	IC1, IC2, IC3, IC5, IC6, IC7, IC9, IC10, IC11, IC42, IC43	11	TE	Digikey	1-2199298-3	
IC socket, 16pin	IC4, IC8, IC12-IC17, IC19, IC20, IC22, IC23, IC25, IC26, IC28, IC29, IC31, IC32, IC34, IC35, IC37, IC38, IC40	23	TE	Digikey	1-2199298-4	
Connector, SODIMM 200	CN1	1	TE	Digikey	1473149-4	
Header, 3POS, 2.54mm LS	FAN	1	Molex	Digikey	22-04-5032	
Header, 4POS, 2.54mm LS	OLED	1	Molex	Digikey	22-04-5042	
Header, 12POS, 2mm LS	DAC, I/O, IO4	3	Molex	Digikey	87831-1220	
Header, 30POS, Male	IO1, IO2, IO3	3	Molex	Digikey	87831-3010	
Header, 10POS, 3.96mm LS	PWR	1	Molex	Digikey	26-64-4100	
VOICE CARDS						
DESCRIPTION	DESIGNATOR	QTY	MANUFACTURER	VENDOR	PART NUMBER	
Resistor 0	R103	8	Stackpole	Digikey	CF14JT00	
Resistor 10	R100, R101, R102, R104, R105, R106	48	Stackpole	Digikey	CF14JT10R0	
Resistor 24	R110, R111	16	Stackpole	Digikey	CF14JT24R0	
Resistor 220	R88, R91, R98, R115	32	Stackpole	Digikey	CF14JT220R	
Resistor 470	R30, R68	16	Stackpole	Digikey	CF14JT470R	
Resistor 680	R108, R109	16	Stackpole	Digikey	CF14JT680R	
Resistor 1k	R31, R32, R69, R117, R119, R128, R138	56	Stackpole	Digikey	CF14JT1K00	
Resistor 1.5k	R22, R23, R60, R61	32	Stackpole	Digikey	CF14JT1K50	
Resistor 2.2k	R19, R57, R71, R131	32	Stackpole	Digikey	CF14JT2K20	
Resistor 2.7k	R24, R62	16	Stackpole	Digikey	CF14JT2K70	
Resistor 3.3k	R42, R78	16	Stackpole	Digikey	CF14JT3K30	
Resistor 4.7k	R70, R157, R158	24	Stackpole	Digikey	CF14JT4K70	
Resistor 6.2k	R18, R56	16	Stackpole	Digikey	CF14JT6K20	
Resistor 10k	R3, R21, R28, R33, R34, R59, R66, R89, R92, R94, R99, R107, R130, R132, R133, R134	128	Stackpole	Digikey	CF14JT10K0	
Resistor 12k	R83	8	Stackpole	Digikey	CF14JT12K0	
Resistor 16.2k	R26, R64	16	Yageo	Digikey	MFR-25FBF52-16K2	
Resistor 18k	R10, R48	16	Stackpole	Digikey	CF14JT18K0	
Resistor 18.2k	R14, R15, R25, R52, R53, R63	48	Yageo	Digikey	MFR-25FBF52-18K2	
Resistor 22k	R40, R41, R76, R77, R112	40	Stackpole	Digikey	CF14JT22K0	
Resistor 28.7k	R29, R67	16	Yageo	Digikey	MFR-25FBF52-28K7	
Resistor 33k	R82	8	Stackpole	Digikey	CF14JT33K0	
Resistor 44.2k	R36, R72	16	Yageo	Digikey	MFR-25FBF52-44K2	
Resistor 47k	R35, R37, R73, R81, R95, R118, R120	56	Stackpole	Digikey	CF14JT47K0	
Resistor 49.9k	R127, R148	16	Yageo	Digikey	MFR-25FBF52-49K9	
Resistor 57.6k	R12, R50	16	Yageo	Digikey	MFR-25FBF52-57K6	
Resistor 59k	R27, R65	16	Yageo	Digikey	MFR-25FBF52-59K0	
Resistor 65.7k	R74	8	Yageo	Digikey	MFR-25FTE52-66K5	
Resistor 68k	R38, R85, R96	24	Stackpole	Digikey	CF14JT68K0	
Resistor 82k	R19, R150	16	Stackpole	Digikey	CF14JT82K0	
Resistor 100k	R1, R2, R6, R9, R11, R44, R47, R49, R80, R84, R86, R87, R90, R93, R97, R114, R116, R123, R124, R125, R126, R129, R135, R136, R137, R151, R152, R153, R154, R155, R156	248	Stackpole	Digikey	CF14JT100K	
Resistor 120k	R39, R75	16	Stackpole	Digikey	CF14JT120K	
Resistor 220k	R4, R159	16	Stackpole	Digikey	CF14JT220K	
Resistor 270k	R122	8	Stackpole	Digikey	CF14JT270K	
Resistor 330k	R121	8	Stackpole	Digikey	CF14JT330K	

Resistor 511k	R20, R58	16	Yageo	Digikey	MFR-25FBF52-511K
Resistor 715k	R8, R46	16	Yageo	Digikey	MFR-25FBF52-715K
Resistor 750k	R16, R54	16	Yageo	Digikey	MFR-25FBF52-750K
Resistor 820k	R17, R55	16	Stackpole	Digikey	CF14JT820K
Resistor 1M	R13	8	Stackpole	Digikey	CF14JT1M00
Resistor 1.5M	R7, R45	16	Yageo	Digikey	MFR-25FBF52-1M50
Resistor 4.7M	R5, R43	16	Yageo	Digikey	MFR-25FBF52-4M70
Capacitor 10pF	C8, C10	16	TDK	Digikey	FG28COG1H100DNT06
Capacitor 100pF	C2, C5, C15	24	Vishay	Digikey	FG26COG2J101JNT06
Capacitor 330pF	C6, C7	16	Cornell Dubilier	Digikey	CD15FD331J03
Capacitor 6.8uF	C16, C18, C23	24	Panasonic	Digikey	EEA-GA1V6R8H
Capacitor 100uF	C22, C24	16	Panasonic	Digikey	EEU-FC1V101
Capacitor 0.1uF	C3, C9, C14	24	Panasonic	Digikey	ECQ-E4104JF
Capacitor 1nF	C13, C17	16	Panasonic	Digikey	ECQ-E6102JF
Capacitor 22nF	C12, C19	16	Panasonic	Digikey	ECQ-E2223JF
Capacitor 47nF	C11, C25	16	Panasonic	Digikey	ECQ-E4473JF
Analog Switch	A7	8	TI	Digikey	CD4053BE
Analog Switch	Rear	8	Vishay	Digikey	DG409DQ-T1-E3
Op Amp, Single JFET	A1, A2, A4, A5	32	TI	Digikey	UA741CP
Op Amp, Single JFET	A6, A8, A9, A16, A17	40	ST	Digikey	TL081CP
Op Amp, Dual JFET	A11	8	ST	Digikey	TL082CP
Voltage Regulator	A21	8	ST	Digikey	7815CV
Voltage Regulator	A20	8	ST	Digikey	7915CV
PNP BJT	Q5, Q6, Q9, Q14, Q15, Q20, Q21, Q22, Q24	72	Central Semi	Digikey	2N3905
JFET	Q3, Q4, Q12, Q13	32	Fairchild	Digikey	J112
LED, Red	D6	8	Kingbright	Digikey	WP7113ID
Diode	D1, D2, D3, D4, D5, D7	48	ON Semi	Digikey	1N4148
Trimpot 100k, 15-Turn	T1, T4	16	Bourns	Digikey	3299Y-1-104LF
Trimpot 10k, 15-Turn	T2, T3, T5, T6, T7, T8	48	Bourns	Digikey	3299Y-1-103LF
Trimpot 100k	T9, T11	16	Bourns	Digikey	3362W-1-104
Trimpot 10k	T10	8	Bourns	Digikey	3362W-1-103
Jumper	+15, -15	16	Harwin	Digikey	D3082-05
IC socket, 8pin	A1, A2, A4, A5, A6, A8, A9, A10, A11, A12, A13, A14, A15, A16, A17	120	TE	Digikey	1-2199298-2
IC socket, 16pin	A7, A18, A19	24	TE	Digikey	1-2199298-4
Header, 10-Pin	D, E	16	Molex	Digikey	09-62-6104
Header, 3-Pin	A, C, G	24	Molex	Digikey	09-48-4039
Header, 4-Pin	F	8	Molex	Digikey	09-48-4049
Header, 8-Pin	B	8	Molex	Digikey	09-48-4089
Capacitor 1nF PS	C1, C4	16	Xicon	Mouser	23P5210
ADSR IC	A18, A19	16	Alfa Rpar	Erica Synth	A53310-DIL
ADSR IC	A18, A19	16	Alfa Rpar	Electric Druid	A53310-DIL
ADSR IC	A18, A19	16	Alfa Rpar	CabinTech	A53310-DIL
Transistor Array	A3	8	Rochester	Rochtec	LM30861, CA3086
OTA, Single	A10, A12, A13, A14, A15	40	Generic	Jameco	LM3080N/CA3080
OTA, Single	A10, A12, A13, A14, A15	40	Generic	Rochtec	LM3080N/CA3080
NPN BJT	Q1, Q2, Q7, Q8, Q10, Q11, Q16, Q17, Q18, Q19, Q23, Q25	96	On Semi/Generic	NA	MP55172
Resistor PTC 1k	R13, R51	16	KRL	Modular Addict	C-2AQ
Resistor PTC 1k	R13, R51	16	KRL	Thonk	C-2AQ

PANELBOARD					
DESCRIPTION	DESIGNATOR	QTY	MANUFACTURER	VENDOR	PART NUMBER
Resistor 10k	R169, R170, R171, R172	4	Stackpole	Digikey	RNF18FTD10K0
Capacitor 10nF	C43, C44	2	TDK	Digikey	FA28COG2A103JRU6
Capacitor 0.1uF	C1, C2, C3, C4, C5, C6, C7, C8, C9, C10, C11, C12, C13, C14, C15, C16, C17, C18, C19, C20, C21, C22, C23, C24, C25, C26, C27, C28, C29, C30, C31, C32, C33, C34, C35, C36, C37, C38, C39, C40, C41, C42	42	TDK	Digikey	FA16COG2A473JRU06
Diode	D1, D2, D3, D4, D5, D6, D7, D8, D9, D10, D11, D12, D13, D14, D15, D16, D17, D18, D19, D20, D21, D22, D23, D24, D25, D26, D27, D28, D29, D30, D31, D32, D33, D34, D35, D36, D37, D38, D39, D40	30	Fairchild	Digikey	1N4148
Encoder	E1	1	Bourns	Digikey	PEC12R-4025F-50024
Analog Switch	IC1, IC2, IC3, IC4, IC5, IC6	6	TI	Digikey	SN74LV4051AN
LED	LED34, LED35, LED36, LED37, LED38, LED39, LED40, LED41, LED42, LED43, LED44, LED45, LED46, LED47, LED48	12	Kingbright	Digikey	WP710A10HD
Push Switch, Black, No LED	SW3, SW5, SW14, SW15	4	C&K	Digikey	SERBKAUOA
Push Switch, Black, No LED	SW3, SW5, SW14, SW15	4	E-Switch	Digikey	5501MBLXX
Push Switch, Black, No LED	SW3, SW5, SW14, SW15	4	Hongju	Hongju Ebay	P886-A0 BLACK
Push Switch, Black, LED	S11, SW1, SW2, SW7, SW8, SW16, SW17, SW18, SW19, SW20, SW21, SW22, SW23, SW24, SW25, SW26, SW27, SW28, SW29, SW31	20	C&K	Digikey	SERLBKRDAUOA
Push Switch, Black, LED	S11, SW1, SW2, SW7, SW8, SW16, SW17, SW18, SW19, SW20, SW21, SW22, SW23, SW24, SW25, SW26, SW27, SW28, SW29, SW31	20	E-Switch	Digikey	5501MBLKRED
Push Switch, Black, LED	S11, SW1, SW2, SW7, SW8, SW16, SW17, SW18, SW19, SW20, SW21, SW22, SW23, SW24, SW25, SW26, SW27, SW28, SW29, SW31	20	Hongju	Hongju Ebay	P886-A1 BLACK
Push Switch, Gray, LED	SW30	1	C&K	Digikey	SERLGYRDAUOA
Push Switch, Gray, LED	SW30	1	E-Switch	Digikey	5501MGRYRED
Push Switch, Gray, LED	SW30	1	Hongju	Hongju Ebay	P886-A1 GRAY
Push Switch, Black, Dual LED	SW4, SW6, SW9, SW10, SW12, SW13	6	C&K	Digikey	SER2LBKRDRDAUOA
Push Switch, Black, Dual LED	SW4, SW6, SW9, SW10, SW12, SW13	6	E-Switch	Digikey	5501MBLKREDRED
Push Switch, Black, Dual LED	SW4, SW6, SW9, SW10, SW12, SW13	6	Hongju	Hongju Ebay	P886-A2 BLACK
Dip Switch, 8 position	VOICES	1	C&K	Digikey	BP408B
Header 20x2	CN78	1	Molex	Digikey	87831-4010
OLED, 128x64	OLED	1	Generic	Generic	

VOICE MOTHERBOARD					
DESCRIPTION	DESIGNATOR	QTY	MANUFACTURER	VENDOR	PART NUMBER
Resistor 100 5% CF	R14, R31, R48, R65	4	Stackpole	Digikey	CF14JT100R
Resistor 499 1% MF	R2, R4, R6, R8, R19, R21, R23, R25, R36, R38, R40, R42, R53, R55, R57, R59, R78, R80, R82, R84	20	Stackpole	Digikey	MFR-25FBF52-499R
Resistor 10k 5% CF	R9, R15, R17, R26, R32, R34, R43, R49, R51, R60, R66, R68	12	Stackpole	Digikey	CF14JT10K0
Resistor 22k 5% CF	R16, R33, R50, R67	4	Stackpole	Digikey	CF14JT22K0
Resistor 23 7k 1% MF	R10, R11, R12, R27, R28, R29, R44, R45, R46, R61, R62, R63	12	Stackpole	Digikey	CMF5023K70DFHEB
Resistor 30k 5% CF	R1, R3, R5, R7, R18, R20, R22, R24, R35, R37, R39, R41, R52, R54, R56, R58, R77, R79, R81, R83, R85, R86, R88, R89	24	Stackpole	Digikey	CF14JT30K0
Resistor 47k 5% CF	R69, R70, R71, R72, R73, R74, R75, R76	8	Stackpole	Digikey	CF14JT47K0
Resistor 100k 5% CF	R13, R30, R47, R64, R87	5	Xicon	Digikey	270-100K-RC
Capacitor 100pF 5% X7R	C13, C19, C25, C31, C49, C50	6	Vishay	Digikey	K101J15COGFS3L2
Capacitor 560pF COG	C9, C10, C11, C12, C15, C16, C17, C18, C21, C22, C23, C24, C27, C28, C29, C30	36	Vishay	Digikey	K560115COGFS3H5
Capacitor 0.1uF 10% X7R	C33, C34, C35, C36, C37, C38, C39, C40, C41, C42, C43, C44, C45, C56, C57, C58	16	Vishay	Digikey	K104K15X7RF53H5
Capacitor 0.47uF PF	C51, C52, C53, C54	4	Panasonic	Digikey	ECQ-E2474JB3
Capacitor 6.8uF Elec	C14, C20, C26, C32	4	Panasonic	Digikey	EEA-FC1V6R8H
Diode, Schottky SOT323	D10, D11	2	NXP	Digikey	BAT85
Op Amp, Dual JFET/TL072	IC5, IC8, IC11, IC14, IC19	5	TI	Digikey	TL072CD
Op Amp, Single JFET	IC17	1	TI	Digikey	TL081CP
IC, VCA	IC1, IC2, IC3, IC4, IC18	5	Cool Audio	Cool Audio	V2164
Connector, Phone Jack, Mono	J1, J2, J3, J4, J5, J6, J8, J9, J10, J11, J12, J13, J14	13	Amphenol	Digikey	ACJM-MHDR
Connector, Phone Jack, Stereo	J5, J6	2	Amphenol	Digikey	ACJS-MHDR
Trimpot 100k	TM1, TM2, TM3, TM4	4	Bourns	Digikey	3362P-1-104LF
Header, 3POS, 3.96mm LS	A1, A2, A3, A4, A5, A6, A7, A8, C1, C2, C3, C4, C5, C6, C7, C8	16	Molex	Digikey	26-60-2030

Header, 3POS, 3.96mm LS	G1, G2, G3, G4, G5, G6, G7, G8	8	Molex	Digikey	26-60-4030
Header, 4POS, 1.25mm LS	CN5	1	Molex	Digikey	53047-0410
Header, 4POS, 3.96mm LS	F1, F2, F3, F4, F5, F6, F7, F8	8	Molex	Digikey	26-60-2040
Header, 4POS, 3.96mm LS	PWR1	1	Molex	Digikey	26-60-4040
Header, 8POS, 3.96mm LS	B1, B2, B3, B4, B5, B6, B7, B8	8	Molex	Digikey	26-60-2080
Header, 10POS, 3.96mm LS	D1, D2, D3, D4, D5, D6, D7, D8, E1, E2, E3, E4, E5, E6, E7, E8	16	Molex	Digikey	26-60-2100
POWER SUPPLY					
DESCRIPTION	DESIGNATOR	QTY	MANUFACTURER	VENDOR	PART NUMBER
SMPSU	NA	1	Meanwell	Digikey	RT-125C
Resistor 120 Ohms	R1, R3	2	Stackpole	Digikey	RNF18FTD120
Resistor 1k Ohms	R5	1	Stackpole	Digikey	RNF18FTD1K00
Resistor 1.24k Ohms	R2, R4	2	Stackpole	Digikey	RNF18FTD1K24
Capacitor 0.1uF	C1, C2, C3, C4, C5, C6	6	TDK	Digikey	FA16COG2A473JRU06
Capacitor 10uF	C7, C8, C9, C10	4	Panasonic	Digikey	EEU-FC1H100L
Capacitor 100uF	C11, C12, C13, C14, C15, C16, C17, C18	8	Panasonic	Digikey	EEU-FC1V470
Diode	D1	1	Fairchild	Digikey	1N4148
VREG	IC1	1	ST	Digikey	LM2941T/NOPB
VREG	IC2	1	ST	Digikey	LM2991T/NOPB
VREG	IC3	1	ST	Digikey	LM1086CT-3.3/NOPB
VSUP	IC4	1	Maxim	Digikey	DS1818-10
TRIMMER	TM1, TM2	2	Bourns	Digikey	3363P-1-201LF
Connector, 3Pos	CN1	1	Molex	Digikey	26-60-4060
Connector, 6Pos	CN2	1	Molex	Digikey	26-60-4060
HARDWARE					
DESCRIPTION	DESIGNATOR	QTY	MANUFACTURER	VENDOR	PART NUMBER
Control Knob	NA	21	Selco/Sifam	Selco/Sifam	DRN110-006 BLK
Control Knob	NA	21	Selco/Sifam	Thonk	DRN110-006 BLK
Control Knob	NA	1	Selco/Sifam	Selco/Sifam	DR110-006 BLK
Control Knob	NA	1	Selco/Sifam	Thonk	DR110-006 BLK
Cap. Control Knob	NA	22	Selco/Sifam	Selco/Sifam	C110BLK
Cap. Control Knob	NA	22	Selco/Sifam	Thonk	C110BLK
PCB Guide	NA	16	Bivar	Digikey	DC-400
Fan, 80mm	NA	1	Sanyo	Digikey	109R0805F401
IEC Jack	NA	1	TE	Digikey	6ESRM-3
IEC Power Cord (NA/CA/CH/JP)	NA	1	Qualtek	Digikey	312014-01
IEC Power Cord (UK)	NA	1	Qualtek	Digikey	370001-E01
IEC Power Cord (AU)	NA	1	Qualtek	Digikey	390002-01
IEC Power Cord (Euro)	NA	1	Qualtek	Digikey	398001-01

